

B1.24	KANCELÁRIA	17,66				ČAS	8	9	10	11	12	13	14	15	16	1	0,08	0,29	0,58
			S	9,80	0,15	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	147,00	171,99	191,10	204,33	207,27	204,33	191,10	171,99	147,00				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	-	-	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	0	0	0	0	0	0	0	0	0				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0							
						$\Sigma I_D = Q_W$	147,00	171,99	191,10	204,33	207,27	204,33	191,10	171,99	147,00				
B1.27	KANCELÁRIA	34,07				ČAS	8	9	10	11	12	13	14	15	16	2	0,16	0,57	2,32
			S	-	-	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	0	0	0	0	0	0	0	0	0				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	19,60	0,15	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	1584,66	1484,70	1143,66	682,08	414,54	408,66	382,20	343,98	294,00				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	1584,66	1484,70	1143,66	682,08	414,54	408,66	382,20	343,98	294,00				
B1.28	KANCELÁRIA	35,42				ČAS	8	9	10	11	12	13	14	15	16	2	0,16	0,58	2,32
			S	-	-	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	0	0	0	0	0	0	0	0	0				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	19,60	0,15	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	1584,66	1484,70	1143,66	682,08	414,54	408,66	382,20	343,98	294,00				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	1584,66	1484,70	1143,66	682,08	414,54	408,66	382,20	343,98	294,00				
B1.29	KANCELÁRIA	40,97				ČAS	8	9	10	11	12	13	14	15	16	2	0,16	0,60	1,29
			S	24,96	0,15	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	374,40	438,05	486,72	520,42	527,90	520,42	486,72	438,05	374,40				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	-	-	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	0	0	0	0	0	0	0	0	0				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	374,40	438,05	486,72	520,42	527,90	520,42	486,72	438,05	374,40				
B1.30	KONFERENČNÁ MIESTNOSŤ	37,65				ČAS	8	9	10	11	12	13	14	15	16	12	0,96	1,59	3,08
			S	24,96	0,15	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	374,40	438,05	486,72	520,42	527,90	520,42	486,72	438,05	374,40				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	-	-	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	0	0	0	0	0	0	0	0	0				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	374,40	438,05	486,72	520,42	527,90	520,42	486,72	438,05	374,40				
B1.32	ODDYCHOVÁ MIESTNOSŤ	29,09				ČAS	8	9	10	11	12	13	14	15	16	6	0,48	0,75	3,34
			S	-	-	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	0	0	0	0	0	0	0	0	0				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	26,11	0,15	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	2111,16	1977,98	1523,64	908,70	552,27	544,44	509,18	458,27	391,68				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	2111,16	1977,98	1523,64	908,70	552,27	544,44	509,18	458,27	391,68				
B1.33	KUCHYŇA	82,10				ČAS	8	9	10	11	12	13	14	15	16	30	2,4	3,86	7,54
			S	-	-	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	0	0	0	0	0	0	0	0	0				
			J	19,60	0,15	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	376,32	676,20	984,90	1202,46	1278,90	1202,46	984,90	676,20	376,32				
			V	-	-	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	0	0	0	0	0	0	0	0	0				
			Z	-	-	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	0	0	0	0	0	0	0	0	0				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	376,32	676,20	984,90	1202,46	1278,90	1202,46	984,90	676,20	376,32				
B2.20	OTVORENÁ KANCELÁRIA	118,88				ČAS	8	9	10	11	12	13	14	15	16	12	0,96	2,99	5,04
			S	19,50	0,15	$I_{OS} [W.m^{-2}]$	100	117	130	139	141	139	130	117	100				
						$I_{DS} = A_S \cdot I_{OS}.s [W]$	292,50	342,23	380,25	406,58	412,43	406,58	380,25	342,23	292,50				
			J	-	-	$I_{OJ} [W.m^{-2}]$	128	230	335	409	435	409	335	230	128				
						$I_{DJ} = A_J \cdot I_{OJ}.s [W]$	0	0	0	0	0	0	0	0	0				
			V	-	-	$I_{OV} [W.m^{-2}]$	539	505	389	232	141	139	130	117	100				
						$I_{DV} = A_V \cdot I_{OV}.s [W]$	0	0	0	0	0	0	0	0	0				
			Z	9,75	0,15	$I_{OZ} [W.m^{-2}]$	100	117	130	139	141	232	389	505	539				
						$I_{DZ} = A_Z \cdot I_{OZ}.s [W]$	146,25	171,11	190,13	203,29	206,21	339,30	568,91	738,56	788,29				
			H	-	-	$I_{OH} [W.m^{-2}]$	379	534	640	706	729	706	640	534	397				
$I_{DH} = A_H \cdot I_{OH}.s [W]$	0	0				0	0	0	0	0	0	0	0						
						$\Sigma I_D = Q_W$	438,75	513,34	570,38	609,86	618,64	745,88	949,16	1080,79	1080,79				